

SXU-1 SUP 1.1.5

(SXU1_V010105)

RELEASE NOTES

Date: 20 November 2015

Table of Contents

A. Introduction	3
Update Information	3
B. Known Issues	3
Region settings containing only three regions	3
C. Updating Instructions	4
How to get a Software Update Package.....	4
SXU-1 Update Procedure	4
Precautions	4
Preparing the SD Card	4
Performing the Update	4

A. Introduction

Dear Customers,

We wish to announce the release of Software Update Packet (SUP) 1.1.5 for the Single Axis Unit SXU-1. This maintenance release fixes a potential issue with an unintended region setting to 'Japan'.

Update Information

We highly recommend updating the SXU-1 to this software update package.

Important notice: This software update requires the previous installation of SXU-1 SUP 1.1.4 (SXU1_V010104). Please make sure to have SXU-1 SUP 1.1.4 (SXU1_V010104) installed before installing SUP 1.1.5 (SXU1_V010105).

B. Known Issues

Region settings containing only three regions

In rare cases, the radio region-setting menu contains three regions only after performing a software update. Please perform the software update again to obtain all five regions. Note that region setting is only available for devices including the EMIP300 radio module.

C. Updating Instructions

How to get a Software Update Package

Go to the ARRI website: www.arri.com/ecs/SXU-1

Select the Downloads section and copy the newest software update package onto your computer.

SXU-1 Update Procedure

Precautions

Make sure the power supply of the SXU-1 is stable. The best way to achieve this is by using a fully charged battery.

Preparing the SD Card

Have a FAT16 or FAT32 formatted SD-Card ready. SD and SDHC cards up to 32GB are supported.

Performing the Update

1. Copy the update (.upd) file to ARRI/SXU1/Firmware/ on SD card.
2. Switch off SXU-1 handset.
3. Unscrew grip with a 3mm Allen key.
4. Insert SD card.
5. Switch on SXU-1 handset.
6. Press MENU.
7. Scroll DOWN until FIRMWARE, press ENTER.
8. Select the update file.
9. Press both UPDATE keys simultaneously.
10. LED flashes red and green: update running.
11. LED stops, SXU-1 handset restarts.
12. Update is complete.
13. Switch off SXU-1 handset.
14. Remove SD card.
15. Reattach grip.

Caution: Do not remove the SD card while the packet is being copied to the SXU-1!

The update process takes about five seconds. The SXU-1 will re-start, and the update process is completed.