

Supported Recording Media



Media/Capacity	Model (Revision)	Firmware	Note	ALEXA Classic	ALEXA XR/XT	ALEXA SXT W	ALEXA LF	ALEXA 65	ALEXA Mini	AMIRA
Sony SxS PRO/PRO+				No adapter required	SxS to XR adapter K2.48838.0	SxS to SXR adapter K2.0006338	SxS to SXR adapter K2.0006338			
8 GB	SBP-8 (A)	n/a	discontinued	no longer supported	no longer supported	-	-	-	-	-
16 GB	SBP-16 (A)	n/a	discontinued	no longer supported	no longer supported	-	-	-	-	-
32 GB	SBP-32 (A)	n/a	discontinued	no longer supported	no longer supported	-	-	-	-	-
64 GB	SBP-64 (A, B, C, D)	n/a	discontinued	✓	✓	✓	-	-	-	-
128 GB	SBP-128 (B, C, D)	n/a	discontinued	✓	✓	✓	-	-	-	-
128 GB	SBP-128 (E)	n/a		-	-	✓	-	-	-	-
256GB	SBP-256 (D, E)	n/a		-	-	✓	✓	-	-	-
SanDisk Extreme Pro CFast 2.0					CFast2.0 to XR adapter K2.48839.0				No adapter required	No adapter required
60 GB	SDCFSP-060G	HDX 8.03	discontinued	-	✓	-	-	-	-	✓
120 GB	SDCFSP-120G	HDX 8.03	discontinued	-	✓	-	-	-	✓	✓
128 GB	SDCFSP-128G (A/B)	HDX14.14	discontinued	-	✓	-	-	-	✓	✓
128 GB	SDCFSP-128G (D)	HDX15.01		-	-	-	-	-	✓	✓
256 GB	SDCFSP-256G (D)	HDX15.01 HDX15.02		-	-	-	-	-	✓	✓
512 GB	SDCFSP-512G (D)	CF1502AR CF1504AR	ARRI Edition only K2.0016648	-	-	-	-	-	✓	✓
Angelbird AV PRO AR									No adapter required	No adapter required
256 GB	AVproAR256 ARRI Edition	AR2.27	ARRI Edition only K2.0021432	-	-	-	-	-	✓	✓
Lexar Professional CFast 2.0 3600x (discontinued)						CFast2.0 to SXR adapter K2.0006337			No adapter required	No adapter required
128 GB	32323-128GBVMC 32338-128GBVMB 32338-128GBVMC	20150507 20150507 20160507	discontinued	-	-	-	-	-	✓	✓
256 GB	32324-256GBVMC 32339-256GBVMB 32339-256GBVMC	20150507 20150507 20160507	discontinued	-	-	✓	-	-	✓	✓
Codex Capture Drive XR					No adapter required	XR Capture Drive adapter K2.0008430		XR Capture Drive adapter K2.0008430		
512GB	CDX-3730	all	discontinued	-	✓	✓	-	✓	-	-
Codex Capture Drive SXR						SXR Capture Drive adapter K2.0008429	SXR Capture Drive adapter K2.0008429	SXR Capture Drive adapter K2.0008429		
1 TB	CDX-37019	all		-	-	✓	✓	✓	-	-
2 TB	CDX-37021	all		-	-	✓	✓	✓	-	-

Notes: Other recording media than the ones listed above are typically rejected as "invalid" the camera. For technical reasons, ARRI may cancel support for individual cards/drives without prior notice. Use of cards that are not officially approved and supported may result in interrupted recording or e.g. data loss in case of a power loss event. ARRI assumes no responsibility for incurred losses in connection with the use of unsupported media.

Last update: 15-Jan-19