

## HOME

## FPS

set sensor speed (0.750 - 200.000fps) 24.000fps  
add/delete value

## SDI

*link to MENU > Monitoring > SDI*

## FPS INFO

*lists maximal frame rates for sensor, codec and media*

## TC

view timecode  
edit/reset/set to time

## OPTIONS

Run mode (Rec run, Free run)  
Mode (Regen, Preset, Jam sync)  
Regen source (LTC in, Media) *set by menu*  
Count mode (Non-Dropframe, Dropframe)  
TC Offset (+/-100, 0)

## PROJECT RATE

*link to Menu > Recording > Project Settings*

## SHUTTER

set exposure time/shutter angle  
add/delete value

## SWITCH UNIT

*change to shutter angle/exposure time display*

## EI

set exposure index (160 - 3200ASA; 800ASA)

## IRIS

*view current iris setting (LDS lens required)*

## OPTIONS

Auto iris mode (Center, Integral)  
Auto iris offset (-9/3 to +9/3; 0/3)  
Lens switch triggers auto iris (On, Off)

## ND

set ND filter (ND -, ND 0.6, ND 1.2, ND 2.1)

## LOOK

view look settings

## EDIT (press wheel)

*add/delete/duplicate/rename/export look file and  
browse ARRI's Look Library*

## LOOK CONFIG

Recording processing (Log C, Look)  
EVF/Monitor processing (Log C, Look)  
SDI 1/2 processing (Log C, Look)  
SDI 1/2 color space (REC 709, REC 2020)

## LOOK PARAMETER

*detailed view of CDL and Video Look Parameter values, can  
be edited (only work on a copied look or use a custom look!)*

## WB

set white balance (2.000 - 11.000K; +/-16.0CC)  
add/delete/rename values; press wheel to confirm

## OPTIONS

Auto WB mode (Matrix, Center)  
WB tracking (On, Off)

## AW

*press two times to trigger auto white balance (follow  
instructions on screen)*

## INFO &amp; SYSTEM STATUS

## i

view information on

Version  
System  
Maximum FPS  
Card  
USB  
Network  
Lens  
User button  
EXT sync

Export HW info file  
Export logfiles  
Export update logfiles

## !

*view camera status/alert states*

