cforce mini RF - Cable Guide

Configuration Overview | 4.5.1 / 2023.10

Item Number	Cable Name	Supported Cameras
K2.0025027	Cable CAM (7p) – LBUS (0.3m/1ft)	ALEXA 35, or when using a cforce mini RF motor in CLIENT mode in a daisy chain with other cforce motors.
K2.0015760	Cable CAM (7p) – LBUS (0.5m/1.6ft)	ALEXA 35, or when using a cforce mini RF motor in CLIENT mode in a daisy chain with other cforce motors.
K2.0015756	Cable CAM (7p) – EXT (6p) (0.6m/2ft)	ALEXA Mini, ALEXA Mini LF, AMIRA
K2.0015755	Cable CAM (7p) – EXT (16p) (0.8m/2.6ft)	ALEXA Classic EV, ALEXA XT EV, ALEXA SXT EV. Only works with ALEXA EV cameras, not ALEXA Plus
K2.0034580	Cable CAM (7p) - LCS (5p) (0.8m/2.6ft)	ALEXA Plus cameras including ALEXA Plus, ALEXA XT Plus, ALEXA SXT Plus, ALEXA LF, ALEXA 65
K2.0015758	Cable CAM (7p) – RED CTRL/D-Tap (0.6m/2ft)	RED DSMC2 cameras except those with Base Expander Module. RED DSMC3 cameras (Komodo/V-Rap- tor) with module or break-out cable from 9p Lemo EXT Connector to RED CTRL connector. Supports run/ stop/tally on WCU-4 and Hi-5. Additional RED Camera Control License Key required for further camera control on Hi-5
K2.0015757	Cable CAM (7p) – LANC/D-Tap (0.6m/2ft)	Many cameras with a LANC connector including Canon C300/C500 series, Sony PXW-FX9/FS7 and Blackmagic Ursa Mini Pro
K2.0018814	Cable CAM (7p) – Sony Venice/F55 CTRL/D-Tap (0.6m/2ft)	Sony F5/F55 and Sony Venice. Not compatible with Sony Venice 2, Panasonic Varicam, Panasonic Vari- cam LT
K2.0047268	Cable CAM (7p) - Sony Remote (8p)/D-Tap (0.8m/2.6ft)	Run/stop/tally for Sony Venice and Venice 2. Additional camera control supported on Hi-5 with Sony Camera Control License Key for Hi-5
K2.0015754	Cable CAM (7p) – RS (0.3m/1ft)	Run/stop/tally on all ARRI Cameras and any camera that supports run/stop via a 3p Fischer connector. Can also be used to supply additional power to an LBUS chain
K2.0018813	Cable CAM (7p) – D-Tap (0.5m/1.6ft)	For adding additional power into an LBUS system, or for powering the cforce mini RF without any came- ra connection
K2.0023832	Cable CAM (7p, f) – CAM (7p, m) (0.3m/1ft)	Extension cable for any CAM cable
K2.0015759	Cable CAM (7p) – ENG (12p) (0.3m/1ft)	Broadcast cameras that feature a 12p Hirose Lens connector. Required for remote iris control by Sony or Skaarhoj RCP. Can also be used to inject lens metadata into Sony Venice LENS connector.
	Note: Sony and RED Camera Control Licenses required f	for camera control on Hi-5. ALEXA Remote License Key required for ALEXA/AMIRA camera control on WCU-4.

© 2020 Arnold & Richter Cine Technik GmbH & Co. Betriebs KG. All rights reserved. This material is provided "as is" for information purposes only without any warranty. ARRI assumes no responsibility with regard to the performance or use of the products or typographical errors or inaccuracies of given information. Product specifications are subject to change without notice. For a full listing of all available components consult the price list.



	Camera Control	
Run/Stop?	on Hi-5	on WCU-4
Yes	Yes	Yes
Yes	Yes	No
Yes	No	No
Yes	Νο	No
Yes	Yes	No
Yes	No	No
No	No	No
N/A	N/A	N/A
N/A	N/A	N/A